## SWITCHEX® DRIVER & DIMMER SWITCH

SWITCHEX° combines an LED dimmer switch and LED driver into a single integrated unit. SWITCHEX° accepts 120VAC input and converts it to 24V or 12V DC, all within a standard gang box. With power options up to 100W, it is a true evolutionary step forward for LED lighting. Installations can be simpler with fewer components and no need to conceal a remote LED driver.



## **FEATURES & BENEFITS**

- Simplifies your LED installation
- Eliminates compatibility issues between drivers and switches
- Superior LED dimming performance (100% to 5%)
- Preset dimmer with on/off switch

## **QUICK SPECS**

**Environment** Indoor **Input Voltage** 120VAC

Output Voltage 12VDC & 24VDC models

Connection Type Hardwired

Warranty 5-Year Limited Warranty

Dimming Dimmable

Certification UL Listed 2108

Visit the product page on the website for specification sheets, install guides, IES files, and photometric reports.

24V SWITCHEX® DRIVER & DIMMER SWITCH									
INPUT	OUTPUT	SKU	WATTAGE	CLASS 2	ENVIRONMENT				
120VAC	<b>24</b> VDC	DI-24V-SE-60W	60W	Yes	Indoor / Dry Location				
		DI-24V-SE-100W	100W	Yes	Indoor / Dry Location				

12V SWITCHEX® DRIVER & DIMMER SWITCH									
INPUT	OUTPUT	SKU	WATTAGE	CLASS 2	ENVIRONMENT				
120VAC	<b>12</b> VDC	DI-12V-SE-40W	40W	Yes	Indoor / Dry Location				
		DI-12V-SE-60W	60W	Yes	Indoor / Dry Location				